



TECH SPECS 2015

Venue address:

Mezzanine
444 Jessie St.
San Francisco, Ca.
94103

Venue contacts:

Production Manager/FOH:

Mike Lee
mike@mezzaninesf.com
cell-530.304.3360

House Manager

Ashley Griffin
ashley@mezzaninesf.com

Stage Manager / Event Liaison

Erin Venables
erin@mezzaninesf.com

House Lighting Director:

Trent Jackson
Trentjax@gmail.com

House Video Tech:

Eric Olson
eric@mezzaninesf.com

POWER

- 100amp 3 phase cam-lock service. (120VAC per leg w/ground and neutral).
- This service is shared with our in house dimmer rack,
- We have power-T's but please bring any turn-arounds (gender benders) if you require them - we do not provide turn-arounds.
- A 50amp single phase is available for spider boxes, or smaller distros. We have a breakout for our 50a service in house.

SOUND

For Live shows, Mezzanine has the EAW KF730 line array permanently installed with a Midas 48 channel Legend 3000 at front of house and a 48 channel Midas Siena on monitors.

For Electronic Music shows, Mezzanine has the Funktion One “Res 4” system permanently installed in a “four corners” configuration surrounding the dance floor. Spec for both is listed below.

EAW Line Array (live system)

- KF730 “S.L.A.M.” system (small line array module)
- Six KF730 cabinets per side, flown
- Four SB1000zRi Sub cabinets located under the stage
- Powered by QSC PowerLight Amps
- Control is via one EAW UX8800 processor. The subs can be run off the L/R or off an aux.
- The KF730 lows handle 700 watts and the highs handle 350. Total 1050 per cabinet. 12 cabinets = 12,600 watts. 4 SB1000's at 2000 watts each = 8000 watts. Total system power: 20,600 watts.

Consoles and monitors

Console: Midas Legend 3000, 48 channels

Monitor console: Midas Siena, 48 channels

Snake: 48 channels with 8 return lines

Monitors:

- 8 Radian RMW 1122 “Microwedge 12” Bi-amped wedges.
- 2 Radian RMW 1152 “Microwedge 15” Bi-amped wedges.
- 1 Radian RPX 215 dual 15 subwoofer
- 2 EAW LA325 Bi-amped side fills
- 2 Martin F12 Black line cabinets
- All powered by QSC amps and controlled with BSS MiniDrives.
- 4 channels noise gates
- 4 channels compressors
- 1 TC Electronics Multi effects unit

Processing

1 BSS FCS-960 Graphic EQ

2 channels Universal Audio 1176 compression

2 channels BSS DPR402 compression

- 12 channels Drawmer DL441 compression
- 3 channels DBX 160A compression
- 8 channels Drawmer DS404 noise gates
- 1 Lexicon PCM81 Reverb
- 1 TC Electronics D-Two delay
- 1 Eventide H3000 Harmonizer

Microphones

- 8 Shure SM58
- 6 Shure SM57
- 4 Shure Beta 56
- 1 Shure Beta 52
- 1 Shure SM81
- 1 Shure SM91
- 3 Sennheiser MD421
- 3 Sennheiser E609
- 6 Sennheiser E604
- 1 Sennheiser MD441
- 2 Beyer M88
- 3 Beyer M201
- 1 Audix D6
- 3 Audix D4
- 2 AKG 414
- 2 AKG 451
- 1 Electrovoice RE20
- 6 BSS AR133 active direct boxes
- 6 Whirlwind passive direct boxes

Wireless Microphones

- 4 Sennheiser SKM100-835 G3 mics with G3 receivers

Funktion One (D.J. system)

- The Funktion One system is a five-way system and powered with QSC Powerlight amps.
- Eight “Resolution 4” Mid-Hi loudspeakers arranged in a cross firing “Four Corners” configuration on the dance floor.
- Eight “F – 218” double 18” bass cabinets.
- Four “Infrabass” double 18” sub-bass cabinets.
- The entire system is controlled by one EAW UX8800 digital signal processor.
- Total system power: 26,400 watts

Booth and Equipment

Mezzanine offers a couple custom D.J. booth set-ups according to your events needs:

- Flown Set-up - Booth hangs against wall in the center of the room using a custom black wooden coffin raised on 16’x4’x2’ stage.
- Stage Set-up – Booth is placed front and center on the main stage using a custom booth constructed of steel, wood and rubber.
- Both booths can accommodate up to three turntables, three CDJ1000s and a laptop or FX unit.

Mezzanine D.J. equipment

- Pioneer DJM 900 Nexus Mixer
- Rane TTM 57 (built in Serato)
- Serato SL4 interface
- 4 Pioneer CDJ 2000 NEXUS
- 3 Technics 1210 MK5 turntables with Ortofon Concorde Stylus and needles
- 3 Technics 1210 MK3 turntables with Ortofon Concorde Stylus and needles
- **D.J. Monitors** are 2 Martin F12 Blackline Speakers with 2 Mackie model 1801 powered sub cabinets. Martin cabinets are powered by QSC powerlight amps and controlled with a XTA Processor.

LIGHTING

CONTROL, DIMMING & POWER

Control is from a Road Hog 4

Dimming is from a 24 channel ETC Sensor rack with CEM+ modules. The dimmer patch cannot be changed or altered. Dimmer runs from a 100a 3phase service, camlock output with T's – no turn-arounds. All outputs female.

Please have a distro should you have a floor package. Our stage power is limited and reserved for sound.

US TRUSS

20 Par64 1000w pars on U/S pipe

6x Par RED wash L106

5x Par BLUE wash L079

4x Par AMBER wash L777

5x Par SPECIAL wash L101 (as standard) substitute L707, L793, L201 or NC

2x Source4 Par as blinder

6x Elation Design Spot 250 Pro

3x SGM Flasher 1500w strobe

All washes are IN and OUT. Washes with a center are a single can.

We have in house a **DF50 hazer**, and a **Jem ZR-44 fogger**. We prefer that you use our in-house fogger and hazer for reasons pertaining to our fire alarm system.

DS TRUSS

4x Par64 1k audience wash

4x Par64 1k stage wash in L201 with R119 frost.

2x Par64 special in L181 or L106

3x 26deg source4 575w profiles in L201 + R119 with frame

1x 36deg source4 575w profile in L201 + R119 with frame

Profiles are single patched. Stage wash & Blinders are IN and OUT.

STAGE FLOOR

4x Chrome Par64 1000w MFL

DANCE FLOOR LIGHTING

6x High End System Trackspot BOLT LED moving mirror

2x Martin MX4 moving mirror

4x Chauvet 412z (can be added to stage upon request)

VIDEO

Mezzanine Video Equipment List

- EdiroIV - 4VideoMixer
- EdiroIV - 8VideoMixer
- Christie LX601i 3LCD digital projector-6000 lumens and 3000:1 contrast. Full specs here: <http://www.christiedigital.com/en-us/business/products/projectors/lcd-display/pages/christie-lx601i-3lcd-digital-projector.aspx>
- Epson6500 Projector-1600ANSI Lumens and 75,000:1 contrast ratio
- (3)Samsung50"PlasmaDisplays
- 9'x12'VideoScreen
- (2)InsigniaDVDPlayers
- (1)ToshibaDVDPlayer
- GrizzlyPror - 1CameraRemoteSystem
- SonyDCRHC32VideoCamera
- 6SurveillanceCameras
- SPCcontrolsCatlincCat5Transmitter/Receiver - CompositeSignal

STAGE

- 24' x 20' permanent hardwood corner stage. (A 4 foot stage extension is also available for bigger productions making it 24' x 24').
- 42" high
- Stage to ceiling height: 10' (some areas of the stage have 12' of clearance)
- ***There is a concrete beam mid-stage, which is 10' above stage. Note for screens and large stage props.*
- Floor to Ceiling height: 16.5'
- DS edge to DS truss: 6'
- Stage to US lighting truss 10'8"

BACKDROP

- One raise/lower able backdrop pipe. Hangs behind back lighting truss. Backdrops are limited to our stage specs. Please provide proof of flame retardancy upon load in of any backdrop/cyc/fabric drop. Drops cannot be hung without this certificate.

MISC.

PARKING:

We can reserve parking out front of the venue with enough space for a large tour bus and trailer. Our venue is in a tight urban area, so please take that into consideration if you arrive earlier than originally advanced. It takes some time to clear the zone.